

IYOUHA



Non contractual picture.

AAE IYOUHA UE FP

Type Type	Wall light Applique
Environment Environnement	Indoor Intérieur
Material Matériaux	Alabaster and painted steel Albâtre et acier peint
Lighting system Système d'éclairage	LED Strip 9,6 W/m 2700K - Integrated or deported transfoimer - Phase dimming Bande LED 9,6 W/m 2700K - Transformateur intégré ou deporté - Variation de phase
Voltage Voltage	24V
Wattage Wattage	3,5 W
Luminous flux Flux lumineux	277 lm The alabaster diffuses between 40 and 60% of the light source lumens L'albâtre diffuse entre 40 et 60% des lumens de la source lumineuse
Weight Poids	6,17 lb / 2,8 kg

Dimensions :

Top view



Front view



60

Side view



100

430

IYOUHA®
DESIGN BY ATELIER ALAIN ELLOUZ
MADE IN FRANCE

References PR004048

Warranty 2 years warranty. General terms and conditions of sale.
Garantie 2 ans de garantie. Voir conditions générales de vente.

LIGHTING CONTROL SYSTEM / SYSTÈME DE CONTRÔLE D'ÉCLAIRAGE

FOR DEPORTED TRANSFORMER / POUR TRANSFORMATEUR DÉPORTÉ

To be chosen according to project : DMX, DALI (DT8), TRIAC (phase dimming, setting knobs to choose the light temperature), 1-10V (two 1-10V bus required), NONE (setting knob to choose and fix the light intensity and temperature).
À choisir selon le projet : DMX, DALI (DT8), TRIAC (variation sur phase, boutons de réglage pour choisir la température de la lumière), 1-10V (deux 1-10V bus requis), AUCUN (bouton de réglage pour choisir et fixer l'intensité lumineuse et la température de couleur).

For a correct functioning the remote transformer / driver must be placed in an accessible place at maximum 33' / 10 m from the light fixture.

Pour un fonctionnement optimisé, le transformateur / driver déporté doit être placé dans un espace accessible à moins de 10 m de câbles du luminaire.

US PRODUCT SHEET

IYOUHA



Non contractual picture.

AAE IYOUHA US FP

Dimensions :


Top view



Front view



Side view



1-4 15/16"

2 3/8"

3 15/16"

LIGHTING CONTROL SYSTEM FOR DEPORTED TRANSFORMER

To be chosen according to project : DMX, DALI (DT8), TRIAC (phase dimming, setting knobs to choose the light temperature), 1-10V (two 1-10V bus required), NONE (setting knob to choose and fix the light intensity and temperature).

For a correct functioning the remote transformer / driver must be placed in an accessible place at maximum 33' from the light fixture.